

U_{P0}/S₀ Adapter

Converts from 2-core U_{P0} to 4-core S₀.

- 1 internal S₀ port (PTMP connection, DSS-1) via 2-core connection
- Simple installation using Western plugs, a fixed installation ensured via screw terminals
- 2 RJ-45 plugs for ISDN system telephones from the COMfortel series and standard ISDN devices
- LEDs for displaying operational states
- Can be operated as a desktop or wall-mounted device



With the U_{P0}/S₀ adapter, ISDN system telephones from the COMfortel series and standard ISDN devices can be adapted to the U_{P0} port of a PBX. Enables "old" 2-core cables to be useable for ISDN connections.

Features

Functions

- Adapter for connection at a 2-wire-U_{P0} port, transforming to 4-wire S₀ interface
- 1 internal S₀ port with 2 plugs for 2 system or ISDN telephones
- Power supply via the U_{P0} port
- Installation via western plugs, fix installation via screw terminals possible
- LEDs for status indication

Technical Data

- **Operating voltage:** via the U_{P0} port of the PBX
- **Connections:** 1x U_{P0} port for connecting the PBX, 2x S₀ port Euro-ISDN (DSS-1), PTMP
- **Range of the internal S₀ port:** approx. 150 m
- **Case:** plastic, grey
- **Dimensions:** Ø 95 mm x 33 mm
- **Weight:** approx. 100 g.
- **Security:** CE

Scope of supply

- U_{P0}/S₀ Adapter
- U_{P0} connection cable RJ-45/RJ-11 (ca. 4 m)
- User manual
- Mounting material (screws and dowel)

Ordering information

- **Product designation:** U_{P0}/S₀ Adapter
- **Part number:** 90436
- **EAN code:** 4019377904367

Copyright © 2016 Auerswald GmbH & Co. KG
Version 1.0 – Subject to modifications